

## WINDING RESISTANCE MEASUREMENTS ARE IMPORTANT:

One of the most important tests that can be made to determine the condition of a transformer, is to measure its winding resistance(s). Many defects or faults can be identified by this test including overheated or damaged windings, loose mechanical connections, poorly welded bonds, and issues associated with tap-changing mechanisms. The Model 1051WR has been designed to quickly perform winding resistance measurements with a very high degree of accuracy. Nine ranges of output current provide for a very broad resistance measurement capability.

# Model 1051WR

## WINDING RESISTANCE OHMMETER

## FEATURES

- Six-inch Color Touch-screen LCD
- Broad resistance measurement capability
- Temperature compensated measurements
- On board micro-printer and USB interface
- Dual RS485 communication interfaces
- Audible discharge alarm
- Transformer demagnetization function
- Nine ranges of output current

## SPECIFICATIONS

- Measurement Range:** 0 to 20k $\Omega$
- Minimum Resolution:** 0.01 $\mu\Omega$
- Selectable output current:** 20mA, 100mA, 200mA, 1A, 2A, 5A, 10A, 20A, 50A, and Automatic Output
- Accuracy:** 0.2% of reading,  $\pm 0.1\mu\Omega$
- Communications:** USB, Dual RS485
- Internal Memory:** Stores up to 99 data records
- Input Power:** 120VAC  $\pm 10\%$  60Hz  $\pm 1$ Hz
- Operating Environment:**  
-4 °F to 104 °F @  $\leq 80\%$  RH non-condensing
- Dimensions:** L 16.5" x W 12.6" x H 7.9"
- Weight:** 32.6lbs



## Model 1051WR

### ORDERING INFORMATION

Amblyonix Model 1051WR Winding Resistance Ohmmeter, supplied with manual, test cables, power cord, two 10A fuses, printer paper, certificate of conformance, packing list, and warranty card.



**Amblyonix**  
Industrial Instrument Company

20 Republic Road, North Billerica, MA 01862  
800-447-4020 WWW.AMBLYONIX.COM